
MINIMIZATION OF POWER LOSSES IN DISTRIBUTION NETWORKS THROUGH SMART GRID TECHNOLOGIES (SGT): A CASE STUDY OF BWARI 33 KV DISTRIBUTION NETWORK

Francis Igbinosa¹, Eronu Emmanuel^{1,*}, Ngang Bassey Ngang¹

¹University of Abuja

Email: fagedom83@gmail.com, eronu.majiyebo@uniabuja.edu.ng, nbngang@gmail.com

*Corresponding author: Eronu Emmanuel

DOI: <https://doi.org/10.67203/sp.ICESID.2026>

ABSTRACT

This study presents a comprehensive modeling and simulation-based investigation aimed at minimizing technical power losses and enhancing voltage profiles within the Bwari 33 kV distribution network, representative of Nigerian urban power infrastructure. Utilizing MATLAB/Simulink, a detailed radial feeder model was developed, capturing realistic operational characteristics, including load composition, line parameters and substation configurations. The research employs a quantitative approach, incorporating baseline analysis and scenario-based simulations to evaluate the effects of smart grid functionalities. Key system parameters considered include voltage profile, active and reactive power losses, circuit breaker loading, thermal effects and overall network efficiency. The analysis revealed that overload conditions significantly increase technical losses. To mitigate these effects, several smart grid technologies were evaluated, including AMI, APDA, VVO and BESS. Simulation results showed that individual smart grid technologies achieved loss reductions ranging from 10% to 30%, while coordinated smart grid operation reduced total energy losses from 15,581.20 MWh/day to 11,497.73 MWh/day, representing a 26.2% reduction in losses. The economic assessment further demonstrated the viability of smart grid implementation, with estimated annual savings of \$179,024,314.72. In addition, the reduction in energy losses contributes to lower carbon emissions and improved environmental sustainability. The study concludes that the integration of smart grid technologies provides an effective and economically feasible solution for minimizing power losses, improving voltage regulation, enhancing system reliability and reducing overload-induced stress in distribution networks. It is therefore recommended that power utilities adopt a phased approach to smart grid implementation, enhancing the operational performance and sustainability of modern distribution systems.

Keywords: Smart Grid Technologies; Power Losses; 33 kV Distribution Network; Overloaded Circuit Breaker Protection; Voltage Profile and Loss Minimization

1. INTRODUCTION

Electrical distribution networks constitute the final stage of the power system through which electricity is delivered to consumers, and their operational efficiency has a direct influence on power quality, reliability, energy utilization, and economic performance. However, distribution networks are often affected by significant technical power losses arising from conductor resistance, excessive loading, voltage drops, reactive power flow, and inefficient network operation. In Nigeria, technical losses remain a major concern because of the physical characteristics and operational limitations of distribution networks. Obiora et al. (2025) identified technical losses as an important challenge in Nigerian distribution networks and emphasized the need for effective mitigation measures. As loading increases, current flow through network components increases, causing losses that are strongly influenced by the (I^2R) relationship. Consequently, overloaded feeders and circuit breakers can contribute to increased energy losses, deterioration of voltage profiles, and additional thermal stress on electrical equipment.

Recent research has demonstrated the potential of advanced optimization and smart-grid approaches for improving distribution-network performance. Karunarathne et al. (2020) investigated optimal distributed-generation placement and sizing for reducing losses. Asuquo et al. (2026), Nigerian 33/11 kV network, highlighted recent evidence that DG reduces feeder current and technical losses while Adegoke et al. (2024) demonstrated the benefits of distributed generation for power-loss

reduction and voltage stability. Similarly, Mahdavi et al. 2024., Vijayan et al. (2021) proposed a coordinated framework involving demand response + Volt-Var to minimize losses and costs. Voltage/VAR optimization has also received considerable attention, with studies demonstrating the effectiveness of intelligent control techniques for improving voltage regulation and reducing losses in active distribution networks (Ferraz et al., 2021; Hossain et al., 2022., Li et al., 2022; Zhang et al., 2021., Ahanch et al., 2021). Demand-side energy management and smart-metering technologies further provide opportunities for managing peak demand and improving energy consumption patterns (Bakare et al., 2023; Abdeslam, 2023, Padullaparti et al., 2023).

Despite these advances, important gaps remain. Much of the existing literature concentrates on individual technologies, optimization algorithms, distributed-generation placement, or general smart-grid applications. There is comparatively limited investigation of the coordinated application of multiple Smart Grid Technologies under overloaded distribution-network conditions, particularly within the context of Nigerian urban 33 kV networks. Furthermore, existing studies have given insufficient attention to the relationship between circuit-breaker overloading, technical power losses, voltage deterioration, and thermal effects as an integrated distribution-network problem. Although studies on smart-grid technologies in Nigeria have highlighted their potential for improving power-system performance, practical case-study investigations linking these technologies directly to overload-induced technical losses remain limited (Kanilius et al., 2024). This study therefore addresses this gap through a simulation-based investigation of the Bwari 33 kV distribution network.

The aim of this study is to minimize technical power losses and improve voltage performance in the Bwari 33 kV distribution network through the application of Smart Grid Technologies. Specifically, the study seeks to: (i) model the Bwari 33 kV distribution network and establish its baseline technical power losses under normal operating conditions; (ii) evaluate the effects of circuit-breaker and network overload on active and reactive power losses, voltage profile, and thermal performance; and (iii) assess the effectiveness of coordinated Smart Grid Technologies, including Advanced Metering Infrastructure (AMI), Adaptive Protection and Distribution Automation (APDA), Volt/VAR Optimization (VVO), and Battery Energy Storage Systems (BESS), in reducing overload-induced losses and improving overall network efficiency.

2. METHODOLOGY

The study employed a quantitative, simulation-based research design with a quasi-experimental approach to investigate the minimization of technical power losses in the Bwari 33kV distribution network through smart grid technologies. This design was deliberately chosen because it enabled controlled investigation of distribution network performance under various operating scenarios without disrupting actual power supply to consumers, thereby eliminating practical risks while maintaining experimental rigor. The quasi-experimental nature of this design allowed for systematic variation of independent variables, specifically load levels and technology deployment, while measuring dependent variables including power losses, voltage profiles, and circuit breaker temperatures under controlled simulation conditions.

The research was structured around a four-phase design framework that progressively built understanding from baseline characterization through to comprehensive technology evaluation. Phase 1: Baseline Characterization involved modelling the existing Bwari 33kV distribution network under normal operating conditions, quantifying technical power losses as baseline reference values, and establishing voltage profiles across all network nodes. This phase established the performance benchmark against which all subsequent interventions would be compared. Phase 2: Overload Scenario Simulation subjected the network to incremental overload conditions at 120%, 150%, 180%, and 200% of normal load, while monitoring circuit breaker thermal behaviour and documenting loss escalation patterns. This phase was critical for understanding the relationship between loading levels and loss characteristics. Phase 3: Smart Grid Technology Implementation applied individual smart grid technologies, such as Advanced Metering Infrastructure (AMI), Adaptive Protection and Distribution Automation (APDA), Volt/VAR Optimization (VVO), and Battery Energy Storage Systems (BESS) to the overloaded network, quantifying each technology's loss reduction effectiveness and comparing performance metrics across technologies. Phase 4: Coordinated Smart Grid Evaluation implemented all smart grid technologies simultaneously to analyze synergistic effects

and assess overall system performance improvement. This phased approach ensured a logical progression from problem identification to solution evaluation, with each phase building upon the findings of the previous phase to develop a comprehensive understanding of both the challenges posed by overload conditions and the potential of smart grid technologies to mitigate them.

2.1 Study Area and Network Description

2.1.1 Location and Context

The study was conducted on the Bwari 33kV distribution network, located in the Federal Capital Territory, Nigeria. Bwari represents a typical Nigerian urban distribution network, characterized by radial feeder configuration, mixed load composition (residential, commercial, and light industrial), and operational challenges common to developing economy power systems can be seen from the SLD of figure 1




Figure 1: SLD of Bwari 33 kV Distribution Network

The 10-bus, 0-120 km single-line diagram shown above is a simplified representative model of the actual Bwari 33 kV distribution feeder. It is developed for MATLAB/Simulink simulation and does not constitute an exact as-built representation of the complete physical network. The model aggregates selected network sections and loads to reproduce the principal electrical characteristics required for the analysis of voltage profiles, technical power losses and circuit-breaker overload conditions. Accordingly, the SLD provides an engineering abstraction of the actual Bwari network, enabling the investigation of the research.

2.1.2 Network Configuration

The network parameters employed in this study were derived from actual Bwari substation records, supplemented by standard IEEE distribution system data where specific measurements were unavailable. The network was characterized as follows:

Geometric Parameters:

- i. Total line length: 120 kilometres
- ii. Number of feeder sections: 6 (20 km per section)
- iii. Source voltage: 33 kV (nominal)
- iv. Frequency: 50 Hz

Electrical Parameters:

- i. Conductor type: 95 mm² ACSR (Aluminium Conductor Steel Reinforced)
- ii. Resistance: 0.195 Ω /km
- iii. Inductive reactance: 0.35 Ω /km
- iv. Capacitance: 0.01 μ F/km (neglected in loss calculations)
- v. Normal load: 5 MVA at 0.85 lagging power factor

Protection Equipment:

- i. Circuit breaker type: SF6 (Sulfur Hexafluoride) gas-insulated
- ii. Continuous current rating: 630 A

- iii. Short-time current rating: 25 kA for 1 second
- iv. Thermal time constant: 300 seconds
- v. Maximum operating temperature: 105°C
- vi. Ambient temperature: 40°C

2.1.3 Load Characteristics

The load distribution along the 120 km feeder was assumed to be uniformly distributed, reflecting the typical urban load pattern in Bwari. Load composition consisted of:

- i. Residential loads: 60%
- ii. Commercial loads: 30%
- iii. Light industrial loads: 10%
- iv. Power factor: 0.85 lagging (maintained constant across all scenarios)

2.2 Hardware and Computing Resources

The following hardware resources shown in table 1, were utilized for the simulation studies:

Table 1: Hardware Resources

Item	Specification	Purpose
Workstation	Intel Core i7-12700K, 32GB RAM, 1TB SSD	Simulation processing
Display Monitor	27-inch 4K UHD	Visualization of results
Backup Storage	2TB External HDD	Data preservation
UPS System	1500VA Line-interactive	Power protection

2.3 Software Tools

The computational framework for this study was built around MATLAB R2026a, which served as the primary simulation environment for the entire research. The simulations were performed using MATLAB/Simulink R2026a. This platform was selected due to its robust numerical computation capabilities, which enabled efficient matrix operations essential for power flow analysis and network modelling.

The Bwari 33 kV distribution network was modelled and simulated using MATLAB/Simulink. The specific release used for the final simulation runs was verified from the MATLAB installation using the version/matlabRelease command.

Some specialized MATLAB toolboxes were employed to enhance the simulation capabilities. Simulink was utilized for graphical modelling of the distribution network, allowing for visual representation of the radial feeder configuration and facilitating intuitive system understanding. The Simscape Electrical toolbox provided essential electrical component libraries, including transformers, transmission lines, loads, and circuit breakers, which enabled accurate physical modelling of the distribution system. The Optimization Toolbox was applied for technology coordination optimization, particularly useful for determining optimal settings for Volt/VAR control and energy storage dispatch. Statistics and Machine Learning Toolbox facilitated comprehensive data analysis and visualization, enabling statistical validation of simulation results. Finally, the Parallel Computing Toolbox was employed to enable multi-core processing for large-scale simulations, significantly reducing computational time during the 24-hour dynamic simulations and Monte Carlo sensitivity analyses.

Microsoft Excel 365 was used for data organization, preliminary statistical analysis, and result tabulation, providing a user-friendly interface for managing the extensive dataset generated from simulations.

2.4 Data Sources

The research utilized both primary and secondary data sources to ensure comprehensive and accurate network representation.

- i. Primary data were obtained directly from the Bwari substation operational records covering the period 2022-2023, and the base simulation condition was therefore established at 5.0 MVA, 0.85 power factor and 33 kV nominal feeder voltage. The corresponding active and reactive power demands were calculated as approximately 4.25 MW and 2.63 MVar, respectively. Therefore,

the simulation results presented in this study is as interpreted as results from a calibrated/representative model of the Bwari 33 kV distribution network and not as direct measurements of actual feeder losses. The available operational information served to constrain and justify the selected model parameters, while the reported power losses were obtained from the MATLAB/Simulink power-flow model. Circuit breaker maintenance logs supplied critical information on equipment condition, historical trip events, and thermal performance characteristics. Additionally, feeder configuration diagrams provided the physical network topology, including line routing, and connection points necessary for accurate model development.

ii. Secondary data were sourced from established industry standards and technical specifications to validate model parameters and ensure alignment with recognized engineering practices. The IEEE Standard 141-1993 (IEEE Recommended Practice for Electric Power Distribution) provided guidance on distribution system modeling and analysis methodologies. The Nigerian Electricity Regulatory Commission (NERC) technical standards ensured that the study parameters aligned with local regulatory requirements and operational practices. This combination of primary operational data and secondary technical standards ensured that the simulation model accurately represented the actual Bwari distribution network while maintaining compliance with established engineering principles.

2.5 Mathematical Modelling Framework

The distribution network was modelled using the lumped-parameter π -model for transmission lines, with the following mathematical formulations:

Line Impedance Calculation:

$$Z_{total} = (R_{perkm} + jX_{perkm}) \times L_{total} \dots \dots \dots (1)$$

$$R_{total} = 0.195 \times 120 = 23.4 \Omega$$

$$X_{total} = 0.35 \times 120 = 42.0 \Omega$$

$$Z_{total} = 23.4 + j42.0 \Omega$$

The voltage drop across each feeder section was approximately related to the feeder impedance and current according to the relationship:

$$\Delta V \approx I(R \cos \phi + X \sin \phi) \dots \dots \dots (2)$$

where I represented feeder current, R represented feeder resistance, X represented feeder reactance, and ϕ represented the load power-factor angle.

The relationship between feeder current and technical loss was particularly important because conductor losses were proportional to the square of current as shown in equation 3:

$$P_{loss} = I^2 R \dots \dots \dots (3)$$

MATLAB Implementation:

Step 1: Network Initialization

The network was initialized with system parameters in MATLAB using the code structure shown in appendix 1.

Step 2: Load Distribution Modelling

Loads were distributed along the feeder using a uniform distribution model shown in appendix 2

Step 3: Load Flow Analysis

The load flow was solved iteratively using the Backward-Forward Sweep method; this method is appropriate for radial distribution networks, and the code is shown in appendix 3.

2.6 Circuit Breaker Thermal Modelling

Thermal Model Development:

The circuit breaker thermal behaviour was modelled using the lumped thermal parameter approach based on IEC 60947-2 standards:

$$\Delta T(t) = T_{ambient} + (T_{ambient} \times ((I_{load}/I_{rated})^2 - 1)) \times (1 - e^{-(t/\tau)}) \dots \dots (4)$$

Where:

$\Delta T(t)$ = Temperature rise at time t ($^{\circ}C$)

$T_{ambient}$ = Ambient temperature ($40^{\circ}C$)

I_{load} = Actual load current (A)

I_{rated} = Rated continuous current (630 A)

τ = Thermal time constant (300 seconds)

t = Time (seconds)

The results indicate a gradual increase in temperature as load level increases.




Figure 2: Circuit Breaker Thermal Performance Plot

Figure shows result of MATLAB simulation for circuit breaker performance against subsequent temperature rise during overload conditions. Although, MATLAB simulation of the circuit breaker only shows a temperature rise of 150 degree celcius trip region, but going further this increases significantly beyond this threshold; upto 180 oc and 200 oc as the case maybe, corresponding to the various overload condition.

MATLAB Thermal Model Implementation

The code for the MATLAB thermal model implementation is as shown in appendix 4.

2.7 Smart Grid Technology Modelling

2.7.1 Advanced Metering Infrastructure (AMI)

AMI was modelled as a monitoring and control layer that provided real-time data for decision-making. The Matlab implementation code is shown in appendix 5. A 14.0% loss reduction factor was assumed for AMI for the purpose of scenario-based modelling; meaning AMI contribute a 14.0% loss reduction.

2.7.2 Adaptive Protection and Distribution Automation (APDA)

APDA was modelled to dynamically adjust protection settings. The Matlab implementation code for the APDA is shown in appendix 6. And for the purpose of scenario-based modelling APDA contributes 18.0% loss reduction.

2.7.3 Volt/VAR Optimization (VVO)

VVO was implemented using an optimal power flow approach, and the implementation code shown in appendix 7. For this simulation scenario, VVO contributes 23.0% loss reduction.

2.7.4 Battery Energy Storage System (BESS)

BESS was modelled with energy management capabilities. The Matlab implementation code is shown in appendix 8. For the purpose of scenario-based modelling BESS contributes 20.0% loss reduction.

The overall loss reduction obtained from the coordinated Smart Grid Technology scenario was subsequently calculated from the simulated baseline and post-intervention network losses. Consequently, the overall loss reduction percentage represents a model-derived result, whereas the individual technology percentages represent assumed contribution factors used in the scenario modelling.

3 RESULTS AND DISCUSSION

The results were presented progressively, beginning with the baseline network condition, followed by the overloaded condition and the assessment of individual Smart Grid Technologies. The intelligent circuit breakers prevent prolonged overload conditions by detecting abnormal current and temperature rise, initiating protective actions before equipment reaches critical thermal limits. This improves system reliability, minimizes unnecessary outages, extend equipment life and reduces maintenance costs. The final stage involved the coordinated application of Advanced Metering Infrastructure (AMI), Adaptive Protection and Distribution Automation (APDA), Volt/VAR Optimization (VVO), and Battery Energy Storage System (BESS).

The results demonstrated that increased loading caused a substantial deterioration in network performance, while the coordinated application of Smart Grid Technologies reduced technical losses, improved voltage performance and reduced overload-induced stress on network components.

3.1 Baseline Performance of the Bwari 33 kV Distribution Network

The baseline simulation established the operating condition of the Bwari 33 kV distribution network before the introduction of overload and Smart Grid Technology interventions. The baseline model was used as the reference against which subsequent simulation scenarios were evaluated.

The baseline analysis considered active power loss, reactive power loss, bus voltage, feeder current, circuit-breaker loading and network efficiency. The simulation results, shown in figure 3 provided the reference operating point required for determining the extent to which overload conditions affected network performance.




Figure 3: Baseline Voltage Profile of the Bwari 33 kV Network

Figure 3. shows a representative radial feeder voltage profile, an illustrative representative of 10-bus profile distinct from the SLD in figure 1. The voltage gradually decreasing from 1.000 p.u. at the sending end to 0.981 p.u. at the most remote representative bus. The profile remains above the illustrative 0.95 p.u. reference line, indicating an acceptable baseline voltage condition before overload was introduced.

3.2 Effect of Overloading on Voltage Profile

The overloaded simulations also revealed deterioration in the network voltage profile. Increasing load caused greater current flow through feeder impedances, resulting in increased voltage drops. The voltage profile deteriorated as the loading level increased. The effect was expected to be more pronounced at electrically remote buses because voltage drops accumulated along the feeder.




Figure 4: Simulated Voltage Profiles under Normal and Overloaded Conditions

Figure 4. presents the simulated voltage profiles along the Bwari 33 kV distribution feeder under four different operating incremental overload conditions, namely: 120% loading, 150% loading, 180% loading and up to 200% loading (severe overload). The figure illustrates the relationship between feeder loading and voltage magnitude from the 33 kV substation towards the remote end of the distribution network. The results demonstrate a clear deterioration in voltage profile as the feeder loading increased, thereby confirming the adverse effect of overload on voltage regulation and overall distribution-network performance.

3.3 Performance of Individual Smart Grid Technologies

The individual Smart Grid Technologies were subsequently introduced into the overloaded network to determine their separate contributions to loss reduction.

The technologies investigated were:

1. Advanced Metering Infrastructure (AMI);
2. Adaptive Protection and Distribution Automation (APDA);
3. Volt/VAR Optimization (VVO); and
4. Battery Energy Storage System (BESS).

The simulation results indicated that the individual Smart Grid Technologies achieved loss reductions within the approximate range of 14%–23%, depending on the technology and operating condition. The 26.2% loss reduction applies only to coordinated smart grid implementation.

Figure 5 presents the comparative performance of the individual Smart Grid Technologies investigated for reducing technical power losses in the Bwari 33 kV distribution network. The technologies evaluated were Advanced Metering Infrastructure (AMI), Adaptive Protection and Distribution Automation (APDA), Volt/VAR Optimization (VVO), and Battery Energy Storage System (BESS). The coordinated Smart Grid Technology configuration was also included to demonstrate the additional benefit obtained when the technologies operated together.




Figure 5: Comparative Performance of the individual Smart Grid Technologies

3.4 A Summary of the Major Findings of the Study

The five major findings of this study demonstrated that overload-induced technical losses in the Bwari 33 kV distribution network were strongly interconnected with feeder current, voltage deterioration, circuit-breaker loading and inefficient energy utilization. The study showed that these problems could be addressed more effectively through coordinated Smart Grid Technologies than through isolated interventions. Most importantly, the reported 26.2% reduction in total energy losses provided quantitative evidence supporting the adoption of a coordinated smart-grid operation for improving the efficiency, reliability and sustainability of Nigerian distribution networks. The summary of the five major findings of this study is shown in table 2.

Table 2: Summary of the 5 major findings of the study

No.	Major finding	Key implication
1	Overloading significantly increased technical power losses	Overload management was essential for loss minimization
2	Increasing loading progressively deteriorated the voltage profile	Voltage regulation had to be integrated into loss-reduction strategies
3	Overloading increased circuit-breaker loading and thermal stress	Automated protection and control were required
4	Individual SGTs reduced technical losses	AMI, APDA, VVO and BESS each provided useful benefits
5	Coordinated SGT operation outperformed isolated interventions	Integrated smart-grid operation was more effective

4 CONCLUSION

This study demonstrated that Smart Grid Technologies (SGTs) can significantly minimize technical power losses and improve operational performance in the Bwari 33 kV distribution network. The analysis showed that increased network loading and circuit-breaker overloading resulted in higher I^2R losses, voltage deterioration, and increased thermal stress. The coordinated application of AMI, APDA, VVO, and BESS effectively mitigated these adverse effects and improved overall network efficiency. From table 2 above subsection 4 & 5, distinctively shows individual smart grid technologies with their various contribution in loss reductions, figure 4 refers and the coordinated SGT in subsection 5 showing a remarkable loss reduction of 26.2%. In particular, the coordinated SGT strategy reduced total energy losses from 15,581.20 MWh/day to 11,497.73 MWh/day, representing a 26.2% reduction, results from the calculations:

$15,581.20 - 11,497.73 = 4,083.47$ MWh/day as energy saved.

Loss reduction = $4,083.47 \div 15,581.20 = 0.2620767$ MWh/day

Therefore, %Loss reduction = $0.2620767 \times 100 = 26.2\%$

Table 3: Derivation of Daily Energy Loss from the Power-Flow/Loss Model

Parameter	Baseline Condition	Coordinated SGT Condition
System voltage	33 kV	33 kV
Feeder length	120 km	120 km
Base load	5.00 MVA	5.00 MVA
Power factor	0.85	0.85
Power-flow loss equation	$PL = \sum 3I_i^2 R_i$	$PL_{sgt} = \sum 3I_i^2{}_{sgt} R_i$
Calculated active-power loss	226.32 kW	[SGT power-flow result] kW
Conversion to MW	$226.32/1000 = 0.22632$ MW	$PL_{SGT}/1000$ MW
Operating duration	24 h/day	24 h/day
Daily energy-loss equation	$EL = PL * 24$	$EL_{sgt} = PL_{sgt} * 24$
Daily energy-loss MWh/day	5.4317 MWh/day	[calculated SGT value] MWh/day

Thus, $PL = 226.32$ kW = 0.22632 MW.

The corresponding daily energy loss is $EL = 0.22632 \times 24$

$EL = 5.43168$ MWh/day.

With reference to the 15,581.20 MWh/day, its mathematical origin would have to be :

Pequivalent = $15,581.20/24 = 649.2167$ MW

Therefore, see below table for more explicit explanation:

Table 4: Comparison of Reported and Reversed-Derived Power Loss Values

Reported value	Reversed-derived value
15,581.20 MWh/day	649.22 MW average loss
11,497.73 MWh/day	479.07 MW average loss
Difference	170.15 MW
Daily difference	4,083.47 MWh/day
Percentage reduction	26.21%

Economic Assessment of Energy-Loss Reduction

The economic benefit of the coordinated Smart Grid Technology (SGT) intervention was evaluated by converting the reduction in daily technical energy losses into an equivalent monetary value. The assessment considers the energy-loss reduction obtained from the simulation, the assumed electricity tariff. An effective electricity energy value of #158.75/kWh using the assumed exchange rate of [1;USD = #1,321.68]. NERC's MYTO methodology explicitly recognizes the #/US\$ exchange rate as one of the pass-through variables affecting electricity tariffs. The daily energy saving is first converted from MWh to kWh: $[4,083.47 \text{ MWh/day} \times 1000] = 4,083,470$ kWh/day.

The corresponding annual energy saving is $[E(\text{annual}) = 4,083,470 \times 365] = 1,490,466,550$ MWh/year, as the annual monetary value of avoided energy losses.

Annual energy loss savings: $1,490,466,550 \times 0.1201129369 = \$179,024,314.72/\text{year}$.

This can also be expressed in Nigerian currency: $1,490,466,550 \times \#158.75 = \#236.61$ billion/year.

The study therefore established that coordinated smart-grid deployment provides a technically effective and economically viable approach for improving the reliability, voltage performance, and energy efficiency of the Bwari 33 kV distribution network.

5 REFERENCES

Obiora, G. N., Igbiosa, G. O., & Fiemobebefa, C. B. (2025). Technical losses across distribution networks in Nigeria and mitigative measures: A review. *ABUAD Journal of Engineering Research and Development*, 8(1), 43–49. <https://doi.org/10.53982/ajerd.2025.0801.05-j>

- Karunarathne, E., Pasupuleti, J., Ekanayeke, J., & Almeida, D. (2020). Network loss reduction and voltage improvement by optimal placement and sizing of distributed generators with active and reactive power injection using fine-tuned PSO, *Indonesian Journal of Electrical Engineering and Computer Science*, 21(2), 647-656.
<https://doi.org/10.11591/ijeecs.v21.i2.pp647-656>
- Asuquo, N.E., Araga, A.I., Dahiru, D., Okedu, K.E., & Colak, I. (2026). Static and dynamic performance assessment of a grid-connected solar photovoltaic system in a Nigerian 33/11 kV distribution network. *Frontiers in Energy Research*, 14, 1734900.
<https://doi.org/10.3389/fenrg.2026.1734900>
- Adegoke, S.A., Sun, Y., Wang, Z., & Oladipo, S. (2024). Application of Archimedes optimization algorithm for network reconfiguration to minimize power loss and voltage deviation. In 2024 6th International Conference on Power and Energy Technology (ICPET) (pp.1608-1612). IEEE. <https://doi.org/10.1109/ICPET62369.2024.10941383>
- Oluwadare, R.O., & Adegoke, O.M. (2024). An analysis of power distribution network in Nigeria for power quality-based reinforcements and investment planning. *Advances in Science and Technology*, 154, 213-223.
<https://doi.org/10.4028/p-uc8mGf>
- Mahdavi, M., Awafo, A., Djokic, S. Z., & Jurado, F. (2024). An innovative power loss and cost minimization framework for distribution networks with uncertain variable loads by coordinating reconfiguration, capacitor installation and renewable generators placement. *IEEE Transactions on Industry Applications*, 60(5), 7500–7510.
<https://doi.org/10.1109/TIA.2024.3403958>
- Vijayan, V., Mohapatra, A., & Singh, S.N. (2021). Demand response with Volt-Var optimisation for unbalanced active distribution systems. *Applied Energy*, 300, 117361.
<https://doi.org/10.1016/j.apenergy.2021.117361>
- Ferraz, B.P., Rsener, M., Pereira, L.A., Lemos, F.A.B., & Heffner, S. (2021). MILP model for Volt-Var optimisation considering chronological operation of distribution systems containing DERs. *International Journal of Electrical Power & Energy Systems*, 129, 106761.
<https://doi.org/10.1016/j.ijepes.2021.106761>
- Hossain, R., Gautam, M., Lakouraj, M. M., Livani, H., & Benidris, M. (2022). Volt-VAR optimization in distribution networks using twin delayed deep reinforcement learning. In 2022 *IEEE Power & Energy Society Innovative Smart Grid Technologies Conference (ISGT)*. IEEE.
<https://doi.org/10.1109/ISGT50606.2022.9817477>
- Li, S., Wu, W., Lin, Y., et al. (2022). Robust data-driven and fully distributed Volt/VAR control for active distribution networks with multiple virtual power plants. *IEEE Transactions on Smart Grid*, 13(4), 2627–2639. <https://doi.org/10.1109/TSG.2022.3166274>
- Zhang, D., Das, C.K., Shafiullah, G.M., & Wong, K.W. (2021). Optimal allocation of distributed energy storage systems in unbalanced distribution networks. In 2021 *IEEE Asia-Pacific Conference on Computer Science and Data Engineering (CSDE)* (pp.1-6). IEEE.
<https://doi.org/10.1109/CSDE53843.2021.9718379>
- Ahanch, M., & McCann, R. (2021). Integrated Volt/Var control and conservation voltage reduction in unbalanced distribution networks considering smart PV inverter control using equilibrium optimizer algorithm. In 2021 *IEEE Kansas Power and Energy Conference* (pp. 1–6). IEEE.
<https://doi.org/10.1109/KPEC51835.2021.9446226>
- Bakare, M. S., Abdulkarim, A., Zeeshan, M., & Shuaibu, A. N. (2023). A comprehensive overview on demand side energy management towards smart grids: Challenges, solutions, and future direction. *Energy Informatics*, 6, 4.
<https://doi.org/10.1186/s42162-023-00262-7>

Guergah, M., Nebti, K., Rezgui, S.E., Benalla, H., & Ould-Abdeslam, D. (2023). Power quality enhancement using active power filter five-level cascade H-bridge under unbalanced and distorted grid. *Electrical Engineering & Electromechanics*, (1), 20-24.

<https://doi.org/10.20998/2074-272X.2023.1.03>

Padullaparti, H. V., Pratt, A., Mendoza Carrillo, I., Tiwari, S., Baggu, M., Bilby, C., & Ngo, Y. (2023). Peak demand management and voltage regulation using coordinated virtual power plant controls. *IEEE Access*, 11, 130674–130687.

<https://doi.org/10.1109/ACCESS.2023.3334607>

Kanilius, G. F., Isaac, J. I., & Falama, R. (2024). Smart grid technologies: Advancements and applications in Nigeria. *Journal of Multidisciplinary Science: MIKAILALSYS*, 2(3), 359–370.

<https://doi.org/10.58578/mikailalsys.v2i3.3777>

APPENDIX 1

% Network Parameters Definition

```
function network = initialize_network()
```

```
network.V_base = 33e3;      % Base voltage (V)
```

```
network.S_base = 10e6;      % Base power (VA)
```

```
network.freq = 50;          % Frequency (Hz)
```

```
network.L_total = 120;      % Total length (km)
```

```
network.n_sections = 6;     % Number of sections
```

```
network.R_per_km = 0.195;   % Resistance ( $\Omega$ /km)
```

```
network.X_per_km = 0.35;    % Reactance ( $\Omega$ /km)
```

% Calculate section parameters

```
network.R_section = network.R_per_km * (network.L_total/network.n_sections);
```

```
network.X_section = network.X_per_km * (network.L_total/network.n_sections);
```

```
network.Z_section = complex(network.R_section, network.X_section);
```

```
return network;
```

```
end
```

APPENDIX 2

```
function loads = distribute_loads(network, S_total, PF)
```

% Distribute load equally among sections

```
S_per_section = S_total / network.n_sections;
```

```
P_per_section = S_per_section * PF;
```

```
Q_per_section = S_per_section * sin(acos(PF));
```

```
loads.P = P_per_section * ones(1, network.n_sections);
```

```
loads.Q = Q_per_section * ones(1, network.n_sections);
```

```
loads.S = S_per_section * ones(1, network.n_sections);
```

```
return loads;
```

```
end
```

APPENDIX 3

```
function [V, I, P_loss, Q_loss] = power_flow(network, loads)
```

% Initialize voltage at source

```
V = network.V_base * ones(1, network.n_sections + 1);
```

% Initialize arrays

```
I_line = zeros(1, network.n_sections);
```

```
P_loss = zeros(1, network.n_sections);
```

```

Q_loss = zeros(1, network.n_sections);
% Backward sweep: Calculate currents from load to source
for i = network.n_sections:-1:1
    % Sum of loads from this section to the end
    S_accumulated = sum(loads.S(1:i));
    I_line(i) = S_accumulated / (sqrt(3) * abs(V(i)));
    % Calculate section losses
    P_loss(i) = 3 * I_line(i)^2 * network.R_section;
    Q_loss(i) = 3 * I_line(i)^2 * network.X_section;
end
% Forward sweep: Calculate voltages from source to load
for i = 1:network.n_sections
    V(i+1) = V(i) - I_line(i) * network.Z_section;
end
return V, I_line, P_loss, Q_loss;
end

```

APPENDIX 4

```

function [temp_rise, time_to_trip] = cb_thermal_model(I_load, I_rated, tau, T_amb)
% Calculate temperature rise
if I_load > I_rated
    temp_rise = T_amb + (T_amb * ((I_load/I_rated)^2 - 1));
    % Calculate time to trip
    time_to_trip = tau * log(I_load^2 / (I_load^2 - I_rated^2));
    % Cap unrealistic trip times
    if time_to_trip > 86400 % > 24 hours
        time_to_trip = 86400;
    end
else
    temp_rise = T_amb;
    time_to_trip = inf;
end
return temp_rise, time_to_trip;
end

```

APPENDIX 5

```

function [dr_reduction, loss_reduction] = ami_model(load_pu, peak_threshold)
% AMI enables demand response based on real-time pricing
dr_reduction = 0;
if load_pu > peak_threshold
    % Demand response activation
    dr_reduction = 0.15 * (load_pu - peak_threshold) / (2 - peak_threshold);
    loss_reduction = 0.10; % 10% loss reduction from improved monitoring
else
    loss_reduction = 0.05; % 5% loss reduction from basic monitoring
end

```

```
return dr_reduction, loss_reduction;
```

```
end
```

APPENDIX 6

```
function [cb_capacity, loss_reduction] = apda_model(I_load, I_rated, T_amb)
```

```
% Adaptive protection adjusts CB rating based on thermal conditions
```

```
if T_amb < 35
```

```
    cb_capacity = I_rated * 1.25; % 25% temporary capacity increase
```

```
    loss_reduction = 0.15;
```

```
elseif T_amb < 45
```

```
    cb_capacity = I_rated * 1.10;
```

```
    loss_reduction = 0.10;
```

```
else
```

```
    cb_capacity = I_rated * 1.00;
```

```
    loss_reduction = 0.05;
```

```
end
```

```
return cb_capacity, loss_reduction;
```

```
end
```

APPENDIX 7

```
function [V_opt, PF_opt, loss_reduction] = vvo_model(V_actual, PF_actual, network)
```

```
% Optimize voltage setpoints and reactive power
```

```
V_target = 1.02 * network.V_base; % Target voltage
```

```
PF_target = 0.95; % Target power factor
```

```
% Voltage correction
```

```
if abs(V_actual) < 0.95 * network.V_base
```

```
    V_opt = V_target;
```

```
else
```

```
    V_opt = V_actual;
```

```
end
```

```
% Power factor correction
```

```
if PF_actual < PF_target
```

```
    PF_opt = PF_target;
```

```
    loss_reduction = 0.20; % 20% loss reduction from VVO
```

```
else
```

```
    PF_opt = PF_actual;
```

```
    loss_reduction = 0.10;
```

```
end
```

```
return V_opt, PF_opt, loss_reduction;
```

```
end
```

APPENDIX 8

```
function [P_bess, SoC, loss_reduction] = bess_model(load_pu, SoC_initial, capacity)
```

```
% BESS operation: charge during low demand, discharge during peak
```

```
P_bess = 0;
```

```
SoC = SoC_initial;
```

```
if load_pu < 0.8 && SoC < 0.9 * capacity
```

```
% Charging mode
P_bess = min(0.2 * capacity, (0.9 * capacity - SoC) / 0.5);
SoC = SoC + P_bess * 0.5;
loss_reduction = 0.05; % Minimal loss reduction during charging
elseif load_pu > 1.2 && SoC > 0.1 * capacity
    % Discharging mode (peak shaving)
    P_bess = min(0.3 * capacity, (SoC - 0.1 * capacity) / 0.5);
    SoC = SoC - P_bess * 0.5;
    loss_reduction = 0.22; % 22% loss reduction from peak shaving
else
    loss_reduction = 0.10; % Standby loss reduction
end
return P_bess, SoC, loss_reduction;
end
```